

## Digital Output 32-Point Processor

## MU-PDOY22

24 Vdc FTA	
Parameter	Specification
FTA Model Numbers	<b>MU-TDOY22, MU-TDOY62</b>
Output Channels	32
Output Type	Open-collector (current sinking) NPN transistors
Load Voltage Range	15-30 Vdc
Load Current	MU-TDOY22 0.5 A (max) per pts. 1.0 A (max) per 2 pts. 5 A (max) per 32 pts.  MU-TDOY62 0.5 A (max) per pts. 1.2 A (max) per 8 pts. 5 A (max) per 32 pts.
Isolation	Galvanic Isolation (photo coupler) 30 Vac, $\pm 42.4$ Vdc max. (Any output voltage referenced to common)
On-State Voltage	0.5 V (max), load current @ 0.5A
Off-State Voltage	30 Vdc (max)
Off-State Leak Current	0.5 $\mu$ A (max)
Turn-On/Turn-Off Time	200 msec (max)
Surge withstand capability	ANSI/IEEE C37.90.1-1978
Load Fuse Rating	MU-TDOY22 -- 1 fuse/2 pts. (compression)* MU-TDOY62 -- 1 fuse/8 pts. (screw terminal)*  * Fuse - 1.6 A 125 V (5.5 x 17.2 MM)

(Continued)

## Digital Output 32-Point Processor (continued)

MU-PDOY22

120/240 Vac Relay FTA																							
Parameter	Specification																						
FTA Model Numbers	<b>MU-TDOY23, MU-TDOY63</b>																						
Output Channels	32 (16 per FTA) 16 isolated Form A (SPST/NO) or Form B (SPST/NC) contacts (jumper selectable per output)																						
Contact Type	Gold-clad silver nickel																						
Maximum Load Voltage	250 Vac (RMS)/125 Vdc																						
Maximum Steady State Load Current per Output	<table> <thead> <tr> <th>Current</th> <th>Voltage</th> </tr> </thead> <tbody> <tr> <td>3 A</td> <td>250 Vac(resistive)</td> </tr> <tr> <td>3 A</td> <td>125 Vac (resistive)</td> </tr> <tr> <td>3 A</td> <td>30 Vdc (resistive)</td> </tr> <tr> <td>1 A</td> <td>48 Vdc (resistive)</td> </tr> <tr> <td>0.4 A</td> <td>125 Vdc (resistive)</td> </tr> <tr> <td>2 A</td> <td>250 Vac (inductive = 0.4 power factor)</td> </tr> <tr> <td>2 A</td> <td>125 Vac (inductive = 0.4 power factor)</td> </tr> <tr> <td>1 A</td> <td>30 Vac (inductive L/R = 100 ms)</td> </tr> <tr> <td>0.3 A</td> <td>48 Vac (inductive L/R = 100 ms)</td> </tr> <tr> <td>0.1 A</td> <td>125 Vac (inductive L/R = 100 ms)</td> </tr> </tbody> </table>	Current	Voltage	3 A	250 Vac(resistive)	3 A	125 Vac (resistive)	3 A	30 Vdc (resistive)	1 A	48 Vdc (resistive)	0.4 A	125 Vdc (resistive)	2 A	250 Vac (inductive = 0.4 power factor)	2 A	125 Vac (inductive = 0.4 power factor)	1 A	30 Vac (inductive L/R = 100 ms)	0.3 A	48 Vac (inductive L/R = 100 ms)	0.1 A	125 Vac (inductive L/R = 100 ms)
Current	Voltage																						
3 A	250 Vac(resistive)																						
3 A	125 Vac (resistive)																						
3 A	30 Vdc (resistive)																						
1 A	48 Vdc (resistive)																						
0.4 A	125 Vdc (resistive)																						
2 A	250 Vac (inductive = 0.4 power factor)																						
2 A	125 Vac (inductive = 0.4 power factor)																						
1 A	30 Vac (inductive L/R = 100 ms)																						
0.3 A	48 Vac (inductive L/R = 100 ms)																						
0.1 A	125 Vac (inductive L/R = 100 ms)																						
Minimum Load Voltage	5 Vdc																						
Minimum Load Current	10 mA																						
Isolation	1500 Vac rms or $\pm 1500$ Vdc Channel-to-channel, and channel-to-PM/APM/HPM common																						
Turn-On Time	10 ms maximum																						
Turn-Off Time	10 ms maximum																						
Maximum Repetition Rate																							
Contact Life	<table> <thead> <tr> <th>Operations</th> <th>% of Max Load</th> </tr> </thead> <tbody> <tr> <td>10,000,000</td> <td>0 (Mechanical Life)</td> </tr> <tr> <td>200,000 @ 3 A</td> <td>(100%)</td> </tr> </tbody> </table>	Operations	% of Max Load	10,000,000	0 (Mechanical Life)	200,000 @ 3 A	(100%)																
Operations	% of Max Load																						
10,000,000	0 (Mechanical Life)																						
200,000 @ 3 A	(100%)																						
FTA +24 Vdc Current	12.5 mA for each energized relay (coil resistance = 2 K $\Omega$ )																						
Surge Absorber for Coil	120 $\Omega$ + 0.03 $\mu$ F for each channel																						
Serviceability	No fuse for FTA																						
Surge withstand capability	ANSI/IEEE C37.90.1-1978																						
NOTE: One FTA supports up to 16 circuits. When 17-32 circuits are used, 2 FTAs are required. Bridge cable MU-KBFT01 or MU-KBFT02 is required to connect the two FTAs.																							